


IMPORTANT - READ CAREFULLY BEFORE INSTALLING FIXTURE. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE.
THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE AND ALL APPLICABLE LOCAL CODES, BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT, AND THE HAZARDS INVOLVED. PROPER GROUNDING IS REQUIRED FOR SAFETY.

8118RF/8128RF/8138RF/8148RF/8148LRF/8168RF

FIXTURE INSTALLATION

- A** - MAKE CUT-OUT IN THE CEILING AS INDICATED (SEE TABLE BELOW).
- B** - REMOVE THE INNER RING BY TURNING COUNTER CLOCKWISE THEN UNCLIP THE CONNECTOR ASSEMBLY.
- C** - OPEN THE CONNECTION BOX BY LOOSENING THE COVER SCREW AND TURNING THE COVER AS SHOWN. INSTALL THE BX CABLE (BY OTHERS) IN THE CONNECTION BOX. MAKE ALL NECESSARY CONNECTIONS BETWEEN THE BRANCH CIRCUIT AND THE LUMINAIRE, AND THEN CLOSE CONNECTION BOX. *FOR OPTIONAL DIMMING 0-10V: WIRES MUST BE RUN THROUGH A SEPARATE CONNECTION BOX. (SEE DRAWING BELOW).
- D** - INSERT FIXTURE IN THE CUT-OUT, STARTING WITH THE WIRING BOX SIDE FIRST.
- E** - FASTEN WASHER & SCREW PARTIALLY TO ANCHOR KEY, LEAVING A SMALL GAP. INSERT ANCHOR KEYS (X2 TYP.) IN CROSS-SHAPED CUT-OUTS AT BOTH ENDS OF MULTIPLE SMALL ASSEMBLY.
- F** - SLIDE ALLEN HEAD SCREW ALONG SLOT, WHEN ANCHOR RESTS ON CEILING SURFACE, TIGHTEN WITH PROVIDED ALLEN HEAD KEY.
- TO ENSURE THE FIXTURE IS TIGHTLY SECURED, PUSH FRAME UPWARDS AGAINST CEILING DURING INSTALLATION.**
- IMPORTANT: PLEASE BE SURE TO ADD ADDITIONAL SUPPORT IF NEEDED IN ORDER TO SAFELY SECURE THE LUMINAIRE TO THE CEILING.**


A




CEILING CUT-OUT

ITEM	CUT-OUT DIMENSIONS (AxB)
8118RF	4-1/2" X 4-1/2"
8128RF	8-1/2" X 4-1/2"
8138RF	12-1/4" X 4-1/2"
8148RF	8-1/2" X 8-1/2"
8148LRF	16" X 4-1/2"
8168RF	23-1/2" X 4-1/2"


B




C




D



E




F



LAMP INSTALLATION

A- CLIP-IN THE TWO CONNECTORS TOGETHER.

B- PLACE INNER RING IN THE INTERMEDIATE RING BY ALIGNING THE TWO PINS WITH THE GAPS AND TURNING CLOCKWISE.



ORDERING INFO

MODEL	LED	OPTIC	VOLTAGE	FINISH	OPTIONAL DIMMING
MODEL					
8118RF - No plaster frame required					
8128RF - **					
8138RF - **					
8148RF - **					
8148LRF - **					
8168RF - **					
	LED	OPTIC	VOLTAGE	FINISH	OPTIONAL DIMMING
	027* - 2700K, 97CRI	SP - 22°	120 - 120V	01 - White	
	927 - 2700K, 90CRI	NF - 29°	UNV - 120-277V	02 - Black	
	030* - 3000K, 97CRI	FL - 40°		10 - Gray	
	830 - 3000K, 80CRI	WF - 60°			OPTIONAL DIMMING
	930 - 3000K, 90CRI				LTE - Leading (TRIAC) and trailing edge (ELV) for 120V only
	835 - 3500K, 80CRI				D10 - 0-10V
	935 - 3500K, 90CRI				
	840* - 4000K, 80CRI				

* LED options may require a longer lead time than standard. Please contact factory for details.

**Refers to NO PLASTER FRAME REQUIRED